

EndPage

The **EndPage** function informs the device that the application has finished writing to a page. This function is typically used to direct the device driver to advance to a new page. This function replaces the NEWFRAME printer escape.

```
int EndPage(  
    HDC hdc          // handle of device context  
);
```

Parameters

hdc

Identifies the device context for the print job.

Return Value

If the function succeeds, the return value is greater than zero.

If the function fails, the return value is less than or equal to zero. To get extended error information, call [GetLastError](#).

Remarks

Use the [ResetDC](#) function to change the device mode, if necessary, after calling the **EndPage** function. Note that a call to **ResetDC** resets all device context attributes back to default values.

Windows NT: Beginning with Windows NT Version 3.5, neither **EndPage** or **StartPage** resets the device context attributes. Device context attributes remain constant across subsequent pages. You do not need to re-select objects and set up the mapping mode again before printing the next page; however, doing so will produce the same results and reduce code differences between Windows 95 and Windows NT.